


## INSTALLATION INSTRUCTIONS

For DOCK140 Series USB Chargers (electrical rating: DC 5V 4.2A)

**CAUTION: To prevent the risk of fire and electric shock, please be sure to read all instructions before installing or using this unit.**



### IMPORTANT SAFETY INSTRUCTIONS

**WARNING – To reduce the risk of fire, electric shock, or injury to persons:**

1. Use the unit for indoor only.
2. Do not use extension cord(s) that is not supplied by National Lighting to connect the unit(s).
3. Do not try to open the unit for any reason.

### MOUNTING

#### RECESS-MOUNT

1. Bore a  $\varnothing 1-5/16"$  (33 mm) hole on the mounting surface. For DOCK141 models, the thickness of the surface cannot exceed 1" (25.4 mm).
2. Push the charger through the hole until it is locked in place.
3. Connect the input cord to the input jack on the bottom of the DOCK140.  
For DOCK141 models, connect the input cord to the input jack on the side of the product.

#### RECESS-MOUNT WITH OPTIONAL MOUNTING BRACKET

1. Bore a  $\varnothing 1-1/2"$  (38 mm) hole on the mounting surface. For DOCK141 models, the thickness of the surface cannot exceed 1" (25.4 mm).
2. Push the mounting bracket through the hole and use three of the included screws to secure it.
3. Align the spring clips on the charger with the notches on the mounting bracket.  
Push the charger until it is locked in place.
4. Connect the input cord to the input jack on the bottom of the DOCK140.  
For DOCK141 models, connect the input cord to the input jack on the side of the product.

#### FLUSH-MOUNT (for models with flushed faceplate)

1. Route a  $\varnothing 2.22"$  (56.40 mm) x 0.08" (2 mm) deep step for the faceplate.
2. At the center of the step, bore a  $\varnothing 1-5/16"$  (33 mm) hole on the mounting surface.  
For DOCK141 models, the thickness of the surface cannot exceed 1" (25.4 mm).
3. Push the charger through the hole until it is locked in place.
4. Connect the input cord to the input jack in the back of the DOCK140.  
For DOCK141 models, connect the input cord to the input jack on the side of the product.

### USING THIS USB CHARGER

1. Plug the power adapter to nearest wall outlet.
2. Connect the USB type A connector from the mobile device to the charger. The charging power of each port cannot exceed DC 5V, 2.1A (approx. 10W).

**Please contact with National Lighting Corp. at (562) 921-0056 for assistance if any question occurs during installation.**