



## INSTALLATION INSTRUCTIONS

Model: TV12100-152-M-4.2A-TR-BK

Rating: AC 125V, 60Hz, 15A

USB Output: DC 5V, 4.2A

### **CAUTION:**

*To prevent the risk of fire and electric shock, please be sure to read all instructions before installing or using this unit.*

### **WARNING:**

*To reduce the risk of fire, electric shock or injury to persons:*

- For indoor use only
- Do not use with extension cords
- Do not plug a device or devices into receptacles that exceed a total of 15A (1800 watts)
- Do not open or attempt to open the unit for any reason

### **MOUNTING:**

1. Cut a 3.7"x1.7" (92.0mmx41.0mm) hole on the mounting surface.
2. Set the main unit into the hole and then secure it with four tapping screws.
3. Align the faceplate with the modules on the main unit, push the faceplate against the main unit until it locks into place.
4. Plug power cord to the nearest wall outlet. Make sure the wall outlet is properly grounded.

### **OPERATING INSTRUCTIONS:**

#### **Tamper Resistant Outlets:**

When inserting a plug into a tamper resistant outlet it is important to push with even force on both plug blades. The insertion force should be very similar to that of regular outlet. If excess force is required to insert a plug into a tamper resistant outlet, the blades on the plug may be damaged or may not meet NEMA standards.

#### **USB Charger:**

The unit supplies total of 4.2A (21 watts) DC 5V charging power.

Please do not attempt to connect any device that requires higher power consumption or the unit may be damaged.

Please contact with National Lighting Corp. at (562) 921-0056 for assistance.